


DataTale CR-FD21 SD4.0x2/CFx1 Thunderbolt™ Card Reader

The Lighting Speed for Your Digital Data Storage

Designed for the SD cards and CF cards users, DataTale CR-FD21 Thunderbolt Card Reader provides two SD 4.0 slots and one CF card slot to transfer digital data simultaneously up to 800MB per second. DataTale CR-FD21 Thunderbolt™ Card Reader delivers a new level



performan

ce to SD/CF cards and digital data storage users, and allows massive data move between thunderbolt-equipped host and digital camcorders or digital camera.

The USB card reader reads/writes data once one media, while the CR-FD21 can access three media at the same time. By employing the new Thunderbolt[™] technology and SD4.0 card/CF card support, the DataTale CR-FD21 Card Reader

becomes the perfect audio/video/movie/photos/data transfer unit with offloading of spanned clips support, using its two media card slots; and can be accessed at a maximum of 800MB per second, using two SD 4.0 cards and one CF Card simultaneously, like the sound of thunder! The CR-FD21 Thunderbolt Card Reader is bus-powered.

The LED indicators display the data access process. With its compact design, the CR-FD21 can be carried easily.

U bytes	U bytes	64 Dit	1139 test	Reads in:	826,227	DATA 🗘	Data read:	680.08 GB
0 bytes 0 bytes	0 bytes 0 bytes	64 bit 64 bit	1143 test 1146 test	Writes out:	2,510,026		Data written:	2.26 TB
372 KB 2.5 MB	336 KB 596 KB	64 bit 64 bit	233 test 194 test	Reads in/sec:	859		Data read/sec:	798 MB
8 KB	0 bytes	64 bit	249 test	Writes out/sec:	803		Data written/sec:	798 MB
32 KB 32 KB	12 KB 28 KB		1075 test 1091 test	writes out/sec.	005		Jata Witten/sec.	7 50 100

Features

- Connects via Thunderbolt[™] ports, up to 10 Gbps data transfer rate
- Supports 2 x SD 4.0 card and 1 x CF card simultaneously, up to 800Mbps transfer rate
- Compatible with Time Machine (Apple) for backups and file protection
- · Provides multiple media slots with increased speed and flexibility
- Monitors data transfer status via LED indicators
- · Dissipates heat efficiently with aluminum housing
- Plug-n-play connection

^{1.} Thunderbolt and the Thunderbolt logo are trademarks of Intel Corporation in the US and other countries.

Data Watch Technologies Co., Ltd.

5F, No. 1, Lane 3, Jihu Road, Neihu, Taipei 114, Taiwan Tel: 886-2-8797 8868 | Fax: 886-2-8797 4801 | http://www.datawatchtech.com | info@datawatchtech.com



Specifications

Model No.	CR-FD21				
	SD card, up to SD4.0,				
	SDHC, SDHC UHS-I,				
	SDXC, SDXC UHS-I,				
Media Support	SDXC UHS-II				
	CF card,				
	CF Type I (UDMA 0-6),				
	CF Type II (UDMA 0-7)				
Memory Slata	SD 4.0 x 2,				
Memory Slots	CF x 1				
Bus Interface	10 Gbps Thunderbolt Up to 800MBps Link / Read / Write				
Data Transfer Speed					
LED Indicator					
Dimension	Body: 110 (W) x 68 (D) x 24 (H) mm				
Dimension	Cable & Connector: 332mm				
Weight	180 g				
	Computer with a Thunderbolt [™] port				
	Mac OS X10.8 or higher Windows 7 or later				
System Requirements	*To operate CR-FD21 under Windows 7,				
	the USB 3.0 Host Driver is required.				

^{1.} Thunderbolt and the Thunderbolt logo are trademarks of Intel Corporation in the US and other countries.

Data Watch Technologies Co., Ltd.